

Component-Level Information Packet

for 08591-60027

Counterlock

Copyright © 1991 Hewlett-Packard Company

**All Rights Reserved.
Reproduction, adaptation, or translation
without prior written permission
is prohibited, except as allowed
under the copyright laws.**

HP Document Part Number 08591-90028

**Printed September 1990
Printed in USA**

**The information contained in this document is subject to change
without notice.**



HP Part Number 08591-60027
Counterlock

Reference Designation	HP Part Number	C D	Qty	Description	Mfr Code	Mfr Part Number
C1	0180-3846	0	1	CAP-FXD 15uF +-10% 25 V TA	04200	299D156X9025DB1
C2	0180-3846	0	1	CAP-FXD 15uF +-10% 25 V TA	04200	299D156X9025DB1
C3	0160-5422	0	1	CAP-FXD 0.047uF 50 V	02010	SA205C473MAAH
C4	0180-3846	0	1	CAP-FXD 15uF +-10% 25 V TA	04200	299D156X9025DB1
C5	0180-3831	3	1	CAP-FXD 10uF +-10% 35 V TA	04200	299D106X9035DB1
C6	0160-4382	9	1	CAP-FXD 3.3pF 200 V	06352	FD12C0G2D3R3C
C7	0160-4554	7	1	CAP-FXD 0.01uF 50 V	02010	SA105C103MAAH
C8	0160-4554	7	1	CAP-FXD 0.01uF 50 V	02010	SA105C103MAAH
C9	0160-4819	7	1	CAP-FXD 2200pF +-5% 100 V CER COG	02010	SA301A222JAAH
C10	0160-5422	0	1	CAP-FXD 0.047uF 50 V	02010	SA205C473MAAH
C11	0160-4517	2	1	CAP-FXD 1.2pF 200 V	06352	FD11C0G2D1R2C
C12	0160-5422	0	1	CAP-FXD 0.047uF 50 V	02010	SA205C473MAAH
C13	0160-4554	7	1	CAP-FXD 0.01uF 50 V	02010	SA105C103MAAH
C14	0160-5422	0	1	CAP-FXD 0.047uF 50 V	02010	SA205C473MAAH
C15	0160-5422	0	1	CAP-FXD 0.047uF 50 V	02010	SA205C473MAAH
C16	0160-3879	7	1	CAP-FXD 0.01uF 100 V	02010	SR201C103MAAH
C17	0160-3879	7	1	CAP-FXD 0.01uF 100 V	02010	SR201C103MAAH
C18	0180-3846	0	1	CAP-FXD 15uF +-10% 25 V TA	04200	299D156X9025DB1
C19	0180-3831	3	1	CAP-FXD 10uF +-10% 35 V TA	04200	299D106X9035DB1
C20	0160-4831	3	1	CAP-FXD 4700pF 100 V	02010	SA101C472KAAH
C21	0160-3879	7	1	CAP-FXD 0.01uF 100 V	02010	SR201C103MAAH
C22	0180-3846	0	1	CAP-FXD 15uF +-10% 25 V TA	04200	299D156X9025DB1
C23	0160-3879	7	1	CAP-FXD 0.01uF 100 V	02010	SR201C103MAAH
C24	0160-4557	0	1	CAP-FXD 0.1uF 50 V	02010	SA305C104MAAH
C25	0160-5422	0	1	CAP-FXD 0.047uF 50 V	02010	SA205C473MAAH
C26	0160-3875	3	1	CAP-FXD 22pF 200 V	06352	FD12C0G2D220J
C27	0160-4554	7	1	CAP-FXD 0.01uF 50 V	02010	SA105C103MAAH
C28	0160-4574	1	1	CAP-FXD 1000pF 100 V	02010	SA101C102KAAH
C29	0160-4554	7	1	CAP-FXD 0.01uF 50 V	02010	SA105C103MAAH
C30	0160-4787	8	1	CAP-FXD 22pF +-5% 100 V CER COG	02010	SA102A220JAAH
C31	0160-4554	7	1	CAP-FXD 0.01uF 50 V	02010	SA105C103MAAH
C32	0160-4801	7	1	CAP-FXD 100pF +-5% 100 V CER COG	02010	SA102A101JAAH
C33	0160-4832	4	1	CAP-FXD 0.01uF 100 V	02010	SA101C103KAAH
C34	0160-4805	1	1	CAP-FXD 47pF +-5% 100 V CER COG	02010	SA102A470JAAH
C35	0160-4803	9	1	CAP-FXD 68pF +-5% 100 V CER COG	02010	SA102A680JAAH
C36	0160-4801	7	1	CAP-FXD 100pF +-5% 100 V CER COG	02010	SA102A101JAAH
C37	0160-4787	8	1	CAP-FXD 22pF +-5% 100 V CER COG	02010	SA102A220JAAH
C38	0160-4801	7	1	CAP-FXD 100pF +-5% 100 V CER COG	02010	SA102A101JAAH
C39	0160-4801	7	1	CAP-FXD 100pF +-5% 100 V CER COG	02010	SA102A101JAAH
C40	0160-4804	0	1	CAP-FXD 56pF +-5% 100 V CER COG	02010	SA102A560JAAH
C41	0160-4801	7	1	CAP-FXD 100pF +-5% 100 V CER COG	02010	SA102A101JAAH
C42	0160-4801	7	1	CAP-FXD 100pF +-5% 100 V CER COG	02010	SA102A101JAAH
C43	0160-5349	0	1	CAP-FXD 200pF +-5% 100 V CER COG	02010	SA101A201JAAH
C44	0160-4574	1	1	CAP-FXD 1000pF 100 V	02010	SA101C102KAAH
C45	0160-4574	1	1	CAP-FXD 1000pF 100 V	02010	SA101C102KAAH
C46	0160-5422	0	1	CAP-FXD 0.047uF 50 V	02010	SA205C473MAAH
C47	0180-3850	6	1	CAP-FXD 68uF 10 V TA	04200	299D686X9010DB1
C48	0160-4662	8	1	CAP-FXD 2700pF +-5% 100 V CER COG	02010	SR301A272JAAH

**Indicates factory-selected value*

HP Part Number 08591-60027
Counterlock

Reference Designation	HP Part Number	C D	Qty	Description	Mfr Code	Mfr Part Number
C49	0160-4574	1	1	CAP-FXD 1000pF 100 V	02010	SA101C102KAAH
C50	0160-4801	7	1	CAP-FXD 100pF +-5% 100 V CER COG	02010	SA102A101JAAH
C51	0160-5422	0	1	CAP-FXD 0.047uF 50 V	02010	SA205C473MAAH
C52	0160-5422	0	1	CAP-FXD 0.047uF 50 V	02010	SA205C473MAAH
C53	0160-5422	0	1	CAP-FXD 0.047uF 50 V	02010	SA205C473MAAH
C54	0160-5422	0	1	CAP-FXD 0.047uF 50 V	02010	SA205C473MAAH
C55	0160-5422	0	1	CAP-FXD 0.047uF 50 V	02010	SA205C473MAAH
C56	0160-5422	0	1	CAP-FXD 0.047uF 50 V	02010	SA205C473MAAH
C57	0160-5422	0	1	CAP-FXD 0.047uF 50 V	02010	SA205C473MAAH
C58	0160-5903	2	1	CAP-FXD 24pF +-5% 200 V CER COG	06352	DA12COG2D240J
C59	0160-5350	3	1	CAP-FXD 300pF +-5% 100 V CER COG	02010	SA101A301JAAH
C60	0160-4801	7	1	CAP-FXD 100pF +-5% 100 V CER COG	02010	SA102A101JAAH
C61	0160-4386	3	1	CAP-FXD 33pF 200 V	02010	SR152A330JAA
C62	0160-4389	6	1	CAP-FXD 100pF 200 V	02010	SR202A101JAAH
C63	0160-4523	0	1	CAP-FXD 16pF 200 V	06352	FD12COG2D160J
C64	0160-4386	3	1	CAP-FXD 33pF 200 V	02010	SR152A330JAA
C65	0160-3874	2	1	CAP-FXD 10pF 200 V	06352	FD12COG2D100D
C66	0160-4386	3	1	CAP-FXD 33pF 200 V	02010	SR152A330JAA
C67	0160-4040	6	1	CAP-FXD 1000pF 100 V	02010	SR201A102JAAH
C68	0160-4040	6	1	CAP-FXD 1000pF 100 V	02010	SR201A102JAAH
C69	0160-4846	0	1	CAP-FXD 1500pF +-5% 100 V CER COG	02010	SA201A152JAAH
C100	0160-4812	0	1	CAP-FXD 220pF +-5% 100 V CER COG	02010	SA101A221JAAH
C101	0160-5422	0	1	CAP-FXD 0.047uF 50 V	02010	SA205C473MAAH
C102	0160-4554	7	1	CAP-FXD 0.01uF 50 V	02010	SA105C103MAAH
C103	0160-4789	0	1	CAP-FXD 15pF +-5% 100 V CER COG	02010	SA102A150JAAH
C104	0160-5422	0	1	CAP-FXD 0.047uF 50 V	02010	SA205C473MAAH
C105	0160-4554	7	1	CAP-FXD 0.01uF 50 V	02010	SA105C103MAAH
C106	0160-4574	1	1	CAP-FXD 1000pF 100 V	02010	SA101C102KAAH
C107	0121-0061	1	1	CAP-VAR 18pF 5.5pF 350 V	01468	304-322-237
C108	0160-4793	6	1	CAP-FXD 6.8pF +-7.35% 100 V CER COG	02010	SA102A6R8DAAH
C109	0160-4554	7	1	CAP-FXD 0.01uF 50 V	02010	SA105C103MAAH
C110	0160-4554	7	1	CAP-FXD 0.01uF 50 V	02010	SA105C103MAAH
C111	0160-4554	7	1	CAP-FXD 0.01uF 50 V	02010	SA105C103MAAH
C112	0160-4554	7	1	CAP-FXD 0.01uF 50 V	02010	SA105C103MAAH
C113	0160-4802	8	1	CAP-FXD 82pF +-5% 100 V CER COG	02010	SA102A820JAAH
C114	0160-5422	0	1	CAP-FXD 0.047uF 50 V	02010	SA205C473MAAH
C115	0180-3844	8	1	CAP-FXD 3.3uF 35 V TA	04200	299D335X9035BB1
C116	0160-4554	7	1	CAP-FXD 0.01uF 50 V	02010	SA105C103MAAH
C117	0160-4574	1	1	CAP-FXD 1000pF 100 V	02010	SA101C102KAAH
C118	0160-4399	8	1	CAP-FXD 0.66pF 50 V	02010	
C119	0160-4574	1	1	CAP-FXD 1000pF 100 V	02010	SA101C102KAAH
C120	0160-4554	7	1	CAP-FXD 0.01uF 50 V	02010	SA105C103MAAH
C121	0160-4557	0	1	CAP-FXD 0.1uF 50 V	02010	SA305C104MAAH
C122	0160-4557	0	1	CAP-FXD 0.1uF 50 V	02010	SA305C104MAAH
C123	0160-4084	8	1	CAP-FXD 0.1uF 50 V	02010	SR215C104MAAH
C124	0160-3879	7	1	CAP-FXD 0.01uF 100 V	02010	SR201C103MAAH
C125	0160-4822	2	1	CAP-FXD 1000pF +-5% 100 V CER COG	02010	SA201A102JAAH

HP Part Number 08591-60027
Counterlock

Reference Designation	HP Part Number	C D	Qty	Description	Mfr Code	Mfr Part Number
C126	0160-4793	6	1	CAP-FXD 6.8pF +-7.35% 100 V CER COG	02010	SA102A6R8DAAH
C127	0160-5699	3	1	CAP-FXD 20pF 100 V	06352	DA12C0G2A200J
C128	0160-4574	1	1	CAP-FXD 1000pF 100 V	02010	SA101C102KAAH
C129	0160-4084	8	1	CAP-FXD 0.1uF 50 V	02010	SR215C104MAAH
C130	0160-4574	1	1	CAP-FXD 1000pF 100 V	02010	SA101C102KAAH
C131	0160-4557	0	1	CAP-FXD 0.1uF 50 V	02010	SA305C104MAAH
C132	0160-4574	1	1	CAP-FXD 1000pF 100 V	02010	SA101C102KAAH
C133	0160-5422	0	1	CAP-FXD 0.047uF 50 V	02010	SA205C473MAAH
C134	0160-5422	0	1	CAP-FXD 0.047uF 50 V	02010	SA205C473MAAH
C135	0160-5422	0	1	CAP-FXD 0.047uF 50 V	02010	SA205C473MAAH
C136	0160-4084	8	1	CAP-FXD 0.1uF 50 V	02010	SR215C104MAAH
C137	0160-5422	0	1	CAP-FXD 0.047uF 50 V	02010	SA205C473MAAH
C138	0160-4822	2	1	CAP-FXD 1000pF +-5% 100 V CER COG	02010	SA201A102JAAH
C139	0160-3879	7	1	CAP-FXD 0.01uF 100 V	02010	SR201C103MAAH
C140	0160-3874	2	1	CAP-FXD 10pF 200 V	06352	FD12C0G2D100D
CR1	1901-1098	1	1	DIODE-SWITCHING 1N4150 50V 200MA 4NS	00746	
CR2	0122-0161	4	1	DIODE-VVC 2.15PF 7% BVR=30V	03334	BB405B
CR3	1901-1098	1	1	DIODE-SWITCHING 1N4150 50V 200MA 4NS	00746	
CR4	1901-1098	1	1	DIODE-SWITCHING 1N4150 50V 200MA 4NS	00746	
CR5	0122-0161	4	1	DIODE-VVC 2.15PF 7% BVR=30V	03334	BB405B
CR6	1901-1098	1	1	DIODE-SWITCHING 1N4150 50V 200MA 4NS	00746	
CR100	1901-1098	1	1	DIODE-SWITCHING 1N4150 50V 200MA 4NS	00746	
CR101	1901-1098	1	1	DIODE-SWITCHING 1N4150 50V 200MA 4NS	00746	
J1	1250-0543	8	1	CONNECTOR-RF SM-SNP M PC 50-OHM	05769	51-053-0349-BE8
J2	1250-0543	8	1	CONNECTOR-RF SM-SNP M PC 50-OHM	05769	51-053-0349-BE8
J3	1252-2162	5	1	CONN-POST TYPE .100-PIN-SPCG 5-CONT	02946	78208-105
J4	1252-1290	8	1	CONN-POST TYPE .100-PIN-SPCG 40-CONT	01380	746867-9
J5	1250-0543	8	1	CONNECTOR-RF SM-SNP M PC 50-OHM	05769	51-053-0349-BE8
J7	1250-0543	8	1	CONNECTOR-RF SM-SNP M PC 50-OHM	05769	51-053-0349-BE8
L1	9100-0539	3	1	INDUCTOR RF-CH-MLD 10UH +-5% .166D-INX.3	03273	15M102J
L2	9100-0539	3	1	INDUCTOR RF-CH-MLD 10UH +-5% .166D-INX.3	03273	15M102J
L3	9100-3560	6	1	INDUCTOR RF-CH-MLD 5.6UH +-5% .166D-INX.	03273	15M561J
L4	9100-2257	6	1	INDUCTOR RF-CH-MLD 820NH +-10% .105D-INX	03273	10M820K
L5	9135-0077	7	1	INDUCTOR 36NH +-6.389% 2.6D-MMX6.6LG-MM	03273	10M036X-1
L9	9100-1632	9	1	INDUCTOR RF-CH-MLD 62UH +-5% .166D-INX.3	03273	15M622J
L10	9100-2260	1	1	INDUCTOR RF-CH-MLD 1.8UH +-10% .105D-INX	03273	10M181K
L11	9100-1632	9	1	INDUCTOR RF-CH-MLD 62UH +-5% .166D-INX.3	03273	15M622J
L12	9100-1641	0	1	INDUCTOR RF-CH-MLD 240UH +-5% .166D-INX.	03273	15M243J
L14	9100-1693	2	1	INDUCTOR RF-CH-MLD 360UH +-5% .2D-INX.45	03273	19M363J
L100	9100-2262	3	1	INDUCTOR RF-CH-MLD 3.9UH +-10% .105D-INX	03273	10M391K
L101	9140-0142	8	1	INDUCTOR RF-CH-MLD 2.2UH +-10% .105D-INX	03273	10M221K
L102	9100-2252	1	1	INDUCTOR RF-CH-MLD 270NH +-10% .105D-INX	03273	10M270K
L103	9100-2891	4	1	INDUCTOR RF-CH-MLD 50NH +-10% .105D-INX.	03273	10M050K-1
L104	9100-2262	3	1	INDUCTOR RF-CH-MLD 3.9UH +-10% .105D-INX	03273	10M391K
L105	9100-2262	3	1	INDUCTOR RF-CH-MLD 3.9UH +-10% .105D-INX	03273	10M391K
L106	9100-2262	3	1	INDUCTOR RF-CH-MLD 3.9UH +-10% .105D-INX	03273	10M391K
L107	9100-2256	5	1	INDUCTOR RF-CH-MLD 560NH +-10% .105D-INX	03273	10M560K
L108	9100-2251	0	1	INDUCTOR RF-CH-MLD 220NH +-10% .105D-INX	03273	10M220K

**Indicates factory-selected value*

HP Part Number 08591-60027
Counterlock

Reference Designation	HP Part Number	C D	Qty	Description	Mfr Code	Mfr Part Number
L109	9100-2262	3	1	INDUCTOR RF-CH-MLD 3.9UH +-10% .105D-INX	03273	10M391K
L110	9100-2262	3	1	INDUCTOR RF-CH-MLD 3.9UH +-10% .105D-INX	03273	10M391K
L111	9100-2262	3	1	INDUCTOR RF-CH-MLD 3.9UH +-10% .105D-INX	03273	10M391K
MP107	5021-8642	3	1	SHIELD - BOTTOM	28480	5021-8642
MP108	5021-8643	4	1	SHIELD - TOP	28480	5021-8643
MP109	0515-0894	3	4	SCREW-MACH M2.5 X 0.45 6MM-LG PAN-HD	01125	
Q1	1855-0555	4	1	TRANSISTOR MOSFET N-CHAN E-MODE SI	02883	VN0300L
Q2	1854-0345	8	1	TRANSISTOR NPN 2N5179 SI TO-72 PD=200MW	02037	2N5179
Q3	1854-0591	6	1	TRANSISTOR NPN SI PD=180MW FT=4GHZ	02037	BFR90
Q4	1854-0720	3	1	TRANSISTOR NPN SI PD=500MW FT=4GHZ	03334	
Q5	1855-0555	4	1	TRANSISTOR MOSFET N-CHAN E-MODE SI	02883	VN0300L
Q7	1855-0278	8	1	TRANSISTOR J-FET 2N5116 P-CHAN D-MODE TO	02883	2N5116
R1	0757-0442	9	1	RESISTOR 10K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R2	0757-0442	9	1	RESISTOR 10K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R3	0757-0416	7	1	RESISTOR 511 +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R4	0757-0199	3	1	RESISTOR 21.5K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R5	0757-0438	3	1	RESISTOR 5.11K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R6	0757-0442	9	1	RESISTOR 10K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R7	0757-0401	0	1	RESISTOR 100 +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R8	0698-0082	7	1	RESISTOR 464 1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R9	0698-7240	3	1	RESISTOR 1.47K +-1% .05W TF TC=0+-100	00746	CRB20
R10	0757-0442	9	1	RESISTOR 10K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R12	0757-0280	3	1	RESISTOR 1K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R13	0698-3157	3	1	RESISTOR 19.6K 1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R14	0757-0420	3	1	RESISTOR 750 +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R15	0698-3157	3	1	RESISTOR 19.6K 1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R16	0698-3444	1	1	RESISTOR 316 1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R17	0757-0419	0	1	RESISTOR 681 +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R18	0698-3430	5	1	RESISTOR 21.5 1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R19	0757-0440	7	1	RESISTOR 7.5K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R20	0757-0394	0	1	RESISTOR 51.1 +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R21	0757-0464	5	1	RESISTOR 90.9K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R22	0757-0280	3	1	RESISTOR 1K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R23	0757-0398	4	1	RESISTOR 75 +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R24	0698-3432	7	1	RESISTOR 26.1 1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R25	0757-0280	3	1	RESISTOR 1K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R26	0757-0280	3	1	RESISTOR 1K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R27	0757-0280	3	1	RESISTOR 1K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R28	0757-0442	9	1	RESISTOR 10K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R29	0698-3432	7	1	RESISTOR 26.1 1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R30	0757-0401	0	1	RESISTOR 100 +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R31	0757-0280	3	1	RESISTOR 1K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R32	0698-7222	1	1	RESISTOR 261 +-1% .05W TF TC=0+-100	00746	CRB20
R33	0757-0442	9	1	RESISTOR 10K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R34	0757-0346	2	1	RESISTOR 10 +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R35	0757-0442	9	1	RESISTOR 10K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R36	0698-3151	7	1	RESISTOR 2.87K 1% .125W TF TC=0+-100	00746	CRB14 OR CRB25

HP Part Number 08591-60027
Counterlock

Reference Designation	HP Part Number	C	D	Qty	Description	Mfr Code	Mfr Part Number
R37	0698-3158	4		1	RESISTOR 23.7K 1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R38	0757-0280	3		1	RESISTOR 1K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R39	0698-3151	7		1	RESISTOR 2.87K 1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R40	0698-3155	1		1	RESISTOR 4.64K 1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R41	0757-0442	9		1	RESISTOR 10K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R42	0698-3136	8		1	RESISTOR 17.8K 1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R43	0757-1094	9		1	RESISTOR 1.47K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R44	0698-0084	9		1	RESISTOR 2.15K 1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R45	0757-0442	9		1	RESISTOR 10K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R46	0757-0199	3		1	RESISTOR 21.5K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R47	0698-7212	9		1	RESISTOR 100 +-1% .05W TF TC=0+-100	00746	CRB20
R51	0757-0394	0		1	RESISTOR 51.1 +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R52	0698-7236	7		1	RESISTOR 1K +-1% .05W TF TC=0+-100	00746	CRB20
R53	0698-3438	3		1	RESISTOR 147 1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R54	0757-0394	0		1	RESISTOR 51.1 +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R55	0698-7222	1		1	RESISTOR 261 +-1% .05W TF TC=0+-100	00746	CRB20
R56	0698-7220	9		1	RESISTOR 215 +-1% .05W TF TC=0+-100	00746	CRB20
R57	0698-7220	9		1	RESISTOR 215 +-1% .05W TF TC=0+-100	00746	CRB20
R58	0698-0085	0		1	RESISTOR 2.61K 1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R100	0757-0442	9		1	RESISTOR 10K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R101	0698-7253	8		1	RESISTOR 5.11K +-1% .05W TF TC=0+-100	00746	CRB20
R102	0698-7243	6		1	RESISTOR 1.96K +-1% .05W TF TC=0+-100	00746	CRB20
R103	0698-7223	2		1	RESISTOR 287 +-1% .05W TF TC=0+-100	00746	CRB20
R104	0757-0394	0		1	RESISTOR 51.1 +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R105	0698-7282	3		1	RESISTOR 82.5K +-1% .05W TF TC=0+-100	00746	CRB20
R106	0698-7242	5		1	RESISTOR 1.78K +-1% .05W TF TC=0+-100	00746	CRB20
R107	0698-7284	5		1	RESISTOR 100K +-1% .05W TF TC=0+-100	00746	CRB20
R108	0698-7282	3		1	RESISTOR 82.5K +-1% .05W TF TC=0+-100	00746	CRB20
R109	0698-7236	7		1	RESISTOR 1K +-1% .05W TF TC=0+-100	00746	CRB20
R110	0757-0394	0		1	RESISTOR 51.1 +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R111	0757-1094	9		1	RESISTOR 1.47K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R112	0698-7282	3		1	RESISTOR 82.5K +-1% .05W TF TC=0+-100	00746	CRB20
R113	0757-1094	9		1	RESISTOR 1.47K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R114	0698-7282	3		1	RESISTOR 82.5K +-1% .05W TF TC=0+-100	00746	CRB20
R115	0698-7243	6		1	RESISTOR 1.96K +-1% .05W TF TC=0+-100	00746	CRB20
R116	0698-7284	5		1	RESISTOR 100K +-1% .05W TF TC=0+-100	00746	CRB20
R118	0698-7241	4		1	RESISTOR 1.62K +-1% .05W TF TC=0+-100	00746	CRB20
R119	0698-7243	6		1	RESISTOR 1.96K +-1% .05W TF TC=0+-100	00746	CRB20
R120	0757-0394	0		1	RESISTOR 51.1 +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R121	0698-7248	1		1	RESISTOR 3.16K +-1% .05W TF TC=0+-100	00746	CRB20
R122	0698-7212	9		1	RESISTOR 100 +-1% .05W TF TC=0+-100	00746	CRB20
R123	0698-7241	4		1	RESISTOR 1.62K +-1% .05W TF TC=0+-100	00746	CRB20
R124	0757-0416	7		1	RESISTOR 511 +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R125	0698-3429	2		1	RESISTOR 19.6 1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R126	0698-7243	6		1	RESISTOR 1.96K +-1% .05W TF TC=0+-100	00746	CRB20
R127	0757-0280	3		1	RESISTOR 1K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R128	0698-7236	7		1	RESISTOR 1K +-1% .05W TF TC=0+-100	00746	CRB20
R129	0698-7243	6		1	RESISTOR 1.96K +-1% .05W TF TC=0+-100	00746	CRB20

**Indicates factory-selected value*

HP Part Number 08591-60027
Counterlock

Reference Designation	HP Part Number	C D	Qty	Description	Mfr Code	Mfr Part Number
R130	0757-0416	7	1	RESISTOR 511 +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R131	0698-7212	9	1	RESISTOR 100 +-1% .05W TF TC=0+-100	00746	CRB20
R132	0757-0416	7	1	RESISTOR 511 +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
T100	9100-4772	4	1	TRANSFORMER-RF FREQ RANGE 3kHz to 800 MH	02739	TM04-2
U1	1820-2921	9	1	IC INV CMOS/74HC HEX	02037	MC74HC04N
U2	1820-3847	0	1	IC DCDR CMOS/74HCT BIN 3-TO-8-LINE	01698	SN74HCT138N
U3	1820-3848	1	1	IC FF CMOS/74HCT D-TYPE POS-EDGE-TRIG CO	01698	SN74HCT374N
U4	1820-3848	1	1	IC FF CMOS/74HCT D-TYPE POS-EDGE-TRIG CO	01698	SN74HCT374N
U5	08590-80105	9	1	PAL PROGRAMMED	28480	08590-80105
U6	1826-1431	6	1	IC V RGLTR-V-REF-FXD 4.9975/5.0025V 8-DI	10858	LT1021CCN8-5
U7	1826-0785	1	1	IC OP AMP LOW-BIAS-H-IMPD DUAL 8-DIP-C	01698	TL072ACJG
U8	1820-6140	2	1	IC DIVR ECL DIV-X-N	01590	SP8716DP
U9	1826-0639	4	1	D/A 8-BIT 16-PLASTIC CMOS	03285	AD7524JN
U10	1826-0785	1	1	IC OP AMP LOW-BIAS-H-IMPD DUAL 8-DIP-C	01698	TL072ACJG
U11	1820-3405	6	1	IC MISC CMOS 4-BIT	02037	MC145146P
U12	1826-0276	5	1	IC V RGLTR-FXD-POS 4.8/5.2V TO-92 PKG	02037	MC78L05ACP
U13	1820-6140	2	1	IC DIVR ECL DIV-X-N	01590	SP8716DP
U14	1820-3007	4	1	IC GATE CMOS/74HC EXCL-OR QUAD 2-INP	02037	MC74HC86N
U15	1826-1913	9	1	IC MISC 8-DIP-P PKG	02910	NE602N
U16	1826-1221	2	1	IC COMPARATOR PRCN 8-DIP-C PKG	03406	LM311J-8
U17	1820-3405	6	1	IC MISC CMOS 4-BIT	02037	MC145146P
U18	1826-0785	1	1	IC OP AMP LOW-BIAS-H-IMPD DUAL 8-DIP-C	01698	TL072ACJG
U19	1820-3237	2	1	IC LCH TTL/ALS TRANSPARENT DUAL 4-BIT	01698	SN74ALS873BNT
U20	1810-0301	4	1	NETWORK-RES 16-DIP 51.0 OHM X 8	02483	761-3-R51
U21	1810-0301	4	1	NETWORK-RES 16-DIP 51.0 OHM X 8	02483	761-3-R51
U22	1810-0301	4	1	NETWORK-RES 16-DIP 51.0 OHM X 8	02483	761-3-R51
U23	1826-0367	5	1	IC V RGLTR-FXD-POS 4.8/5.2V TO-39 PKG	02037	MC78M05CG
U24	1826-1945	7	1	IC DIFF AMPL 8-DIP-P PKG	02910	NE5212N
U100	5086-7806	5	1	SAMPLER ASSEMBLY	28480	5086-7806
U101	1826-1945	7	1	IC DIFF AMPL 8-DIP-P PKG	02910	NE5212N
U102	1826-1945	7	1	IC DIFF AMPL 8-DIP-P PKG	02910	NE5212N
U103	1820-1888	5	1	IC PRESCR ECL	02037	MC12013L
U104	1820-5055	6	1	IC MUXR/DATA-SEL CMOS/74HCT 8-TO-1-LINE	02910	74HCT151N
U105	1820-5602	9	1	IC-PROGRAMMABLE INTERVAL TIMER,DC-10MHZ	03811	P82C54-2
U106	1820-6219	6	1	IC CNTR CMOS/74HCT BIN SYNC/ASYNC POS-ED	02910	74HCT4520N
U107	1826-1946	8	1	IC RF/IF AMPL 8-DIP-P PKG	02037	MC1490P
U108	1820-6215	2	1	IC-INTERFACE RCVR LINE DUAL	01698	SN75207N
U109	1826-0285	6	1	IC V RGLTR-FXD-NEG -4.8/-5.2V TO-92 PKG	02037	MC79L05ACP
U110	1820-3537	5	1	IC FF CMOS/74HCT D-TYPE POS-EDGE-TRIG PR	02910	74HCT74N
Y1	0410-0405	0	1	CRYSTAL-QUARTZ 10.000 MHZ	01409	