

Component-Level Information Packet

for 08590-60158

BW Filter

Copyright © 1991 Hewlett-Packard Company

**All Rights Reserved.
Reproduction, adaptation, or translation
without prior written permission
is prohibited, except as allowed
under the copyright laws.**

HP Document Part Number 08590-90120

**Printed December 1990
Printed in USA**

**The information contained in this document is subject to change
without notice.**



HP Part Number 08590-60158

BW Filter

Reference Designation	HP Part Number	C D	Qty	Description	Mfr Code	Mfr Part Number
C1	0160-4832	4	1	CAP-FXD 0.01uF 100 V	02010	SA101C103KAAH
C2	0160-4832	4	1	CAP-FXD 0.01uF 100 V	02010	SA101C103KAAH
C4	0160-4832	4	1	CAP-FXD 0.01uF 100 V	02010	SA101C103KAAH
C5	0160-4832	4	1	CAP-FXD 0.01uF 100 V	02010	SA101C103KAAH
C6	0160-4811	9	1	CAP-FXD 270pF +-5% 100 V CER COG	02010	SA101A271JAAH
C7	0160-4832	4	1	CAP-FXD 0.01uF 100 V	02010	SA101C103KAAH
C9	0160-4832	4	1	CAP-FXD 0.01uF 100 V	02010	SA101C103KAAH
C10	0160-5899	5	1	CAP-FXD 7.5pF 200 V	06352	DA12C0G2D7R5D
C11	0160-4789	0	1	CAP-FXD 15pF +-5% 100 V CER COG	02010	SA102A150JAAH
C12	0160-4832	4	1	CAP-FXD 0.01uF 100 V	02010	SA101C103KAAH
C13	0160-4799	2	1	CAP-FXD 2.2pF +-11.36% 100 V CER COG	02010	MA101A2R2CAAH
C14	0160-0437	7	1	CAP-FXD 12pF 500 V	09538	301-000-P3K0-120J
C15	0121-0059	7	1	CAP-VAR 8pF 2pF 350 V	01468	304-324-139
C16	0160-4832	4	1	CAP-FXD 0.01uF 100 V	02010	SA101C103KAAH
C17	0121-0059	7	1	CAP-VAR 8pF 2pF 350 V	01468	304-324-139
C18	0160-4832	4	1	CAP-FXD 0.01uF 100 V	02010	SA101C103KAAH
C19	0160-4832	4	1	CAP-FXD 0.01uF 100 V	02010	SA101C103KAAH
C20	0160-4832	4	1	CAP-FXD 0.01uF 100 V	02010	SA101C103KAAH
C21	0160-4832	4	1	CAP-FXD 0.01uF 100 V	02010	SA101C103KAAH
C22	0160-4832	4	1	CAP-FXD 0.01uF 100 V	02010	SA101C103KAAH
C23	0121-0036	0	1	CAP-VAR 18pF 5.5pF 350 V	01468	304-324-237
C24	0140-0205	5	1	CAP-FXD 62pF 300 V MICA	02367	CD15ED620J03
C25	0121-0059	7	1	CAP-VAR 8pF 2pF 350 V	01468	304-324-139
C26	0160-5407	1	1	CAP-FXD 62pF 100 V	02010	SA102A620JAAH
C27	0160-4832	4	1	CAP-FXD 0.01uF 100 V	02010	SA101C103KAAH
C28	0160-4832	4	1	CAP-FXD 0.01uF 100 V	02010	SA101C103KAAH
C29	0160-4835	7	1	CAP-FXD 0.1uF 50 V	02010	SA115C104KAAH
C30	0160-4832	4	1	CAP-FXD 0.01uF 100 V	02010	SA101C103KAAH
C31	0160-4832	4	1	CAP-FXD 0.01uF 100 V	02010	SA101C103KAAH
C32	0160-4786	7	1	CAP-FXD 27pF +-5% 100 V CER COG	02010	SA102A270JAAH
C33	0160-4832	4	1	CAP-FXD 0.01uF 100 V	02010	SA101C103KAAH
C35	0160-4831	3	1	CAP-FXD 4700pF 100 V	02010	SA101C472KAAH
C36	0160-4811	9	1	CAP-FXD 270pF +-5% 100 V CER COG	02010	SA101A271JAAH
C37	0160-4832	4	1	CAP-FXD 0.01uF 100 V	02010	SA101C103KAAH
C38	0121-0059	7	1	CAP-VAR 8pF 2pF 350 V	01468	304-324-139
C39	0160-4789	0	1	CAP-FXD 15pF +-5% 100 V CER COG	02010	SA102A150JAAH
C40	0160-5899	5	1	CAP-FXD 7.5pF 200 V	06352	DA12C0G2D7R5D
C41	0160-4832	4	1	CAP-FXD 0.01uF 100 V	02010	SA101C103KAAH
C42	0160-4832	4	1	CAP-FXD 0.01uF 100 V	02010	SA101C103KAAH
C43	0160-4799	2	1	CAP-FXD 2.2pF +-11.36% 100 V CER COG	02010	MA101A2R2CAAH
C44	0160-0437	7	1	CAP-FXD 12pF 500 V	09538	301-000-P3K0-120J
C45	0121-0036	0	1	CAP-VAR 18pF 5.5pF 350 V	01468	304-324-237
C46	0160-4832	4	1	CAP-FXD 0.01uF 100 V	02010	SA101C103KAAH
C47	0121-0059	7	1	CAP-VAR 8pF 2pF 350 V	01468	304-324-139
C48	0160-4832	4	1	CAP-FXD 0.01uF 100 V	02010	SA101C103KAAH
C49	0160-4832	4	1	CAP-FXD 0.01uF 100 V	02010	SA101C103KAAH
C50	0160-4832	4	1	CAP-FXD 0.01uF 100 V	02010	SA101C103KAAH
C51	0160-4832	4	1	CAP-FXD 0.01uF 100 V	02010	SA101C103KAAH

**Indicates factory-selected value*

HP Part Number 08590-60158
BW Filter

Reference Designation	HP Part Number	C D	Qty	Description	Mfr Code	Mfr Part Number
C52	0140-0205	5	1	CAP-FXD 62pF 300 V MICA	02367	CD15ED620J03
C53	0160-5407	1	1	CAP-FXD 62pF 100 V	02010	SA102A620JAAH
C54	0121-0059	7	1	CAP-VAR 8pF 2pF 350 V	01468	304-324-139
C55	0160-4832	4	1	CAP-FXD 0.01uF 100 V	02010	SA101C103KAAH
C56	0160-4832	4	1	CAP-FXD 0.01uF 100 V	02010	SA101C103KAAH
C57	0160-4835	7	1	CAP-FXD 0.1uF 50 V	02010	SA115C104KAAH
C58	0160-4832	4	1	CAP-FXD 0.01uF 100 V	02010	SA101C103KAAH
C59	0160-4796	9	1	CAP-FXD 3.9pF +-6.4% 100 V CER COG	02010	SA101A3R9CAAH
C60	0160-4832	4	1	CAP-FXD 0.01uF 100 V	02010	SA101C103KAAH
C61	0160-4832	4	1	CAP-FXD 0.01uF 100 V	02010	SA101C103KAAH
C62	0160-4832	4	1	CAP-FXD 0.01uF 100 V	02010	SA101C103KAAH
C63	0160-4832	4	1	CAP-FXD 0.01uF 100 V	02010	SA101C103KAAH
C64	0160-4832	4	1	CAP-FXD 0.01uF 100 V	02010	SA101C103KAAH
C65	0160-4832	4	1	CAP-FXD 0.01uF 100 V	02010	SA101C103KAAH
C66	0160-4832	4	1	CAP-FXD 0.01uF 100 V	02010	SA101C103KAAH
C67	0160-4832	4	1	CAP-FXD 0.01uF 100 V	02010	SA101C103KAAH
C68	0160-4832	4	1	CAP-FXD 0.01uF 100 V	02010	SA101C103KAAH
C69	0160-4832	4	1	CAP-FXD 0.01uF 100 V	02010	SA101C103KAAH
C70	0160-4832	4	1	CAP-FXD 0.01uF 100 V	02010	SA101C103KAAH
C71	0160-4535	4	1	CAP-FXD 1uF 50 V	02010	SR305C105KAAH
C72	0160-4535	4	1	CAP-FXD 1uF 50 V	02010	SR305C105KAAH
C73	0160-4832	4	1	CAP-FXD 0.01uF 100 V	02010	SA101C103KAAH
C74	0160-4832	4	1	CAP-FXD 0.01uF 100 V	02010	SA101C103KAAH
C75	0160-4832	4	1	CAP-FXD 0.01uF 100 V	02010	SA101C103KAAH
C76	0160-4832	4	1	CAP-FXD 0.01uF 100 V	02010	SA101C103KAAH
C77	0160-4832	4	1	CAP-FXD 0.01uF 100 V	02010	SA101C103KAAH
C78	0160-4806	2	1	CAP-FXD 39pF +-5% 100 V CER COG	02010	SA102A390JAAH
C79	0160-4535	4	1	CAP-FXD 1uF 50 V	02010	SR305C105KAAH
C80	0160-4380	7	1	CAP-FXD 1pF 200 V	06352	FD11C0K2D1ROC
CR1	1901-0050	3	1	DIODE-SWITCHING 80V 200MA 2NS DO-35	03334	BAV10 SELECTED
CR2	1901-0050	3	1	DIODE-SWITCHING 80V 200MA 2NS DO-35	03334	BAV10 SELECTED
CR3	1901-1070	9	1	DIODE-PIN 110V	02062	
CR4	1901-0535	9	1	DIODE-SCHOTTKY SM SIG	02062	
CR5	1901-1070	9	1	DIODE-PIN 110V	02062	
CR6	1901-0535	9	1	DIODE-SCHOTTKY SM SIG	02062	
CR7	1901-0050	3	1	DIODE-SWITCHING 80V 200MA 2NS DO-35	03334	BAV10 SELECTED
CR8	1901-0050	3	1	DIODE-SWITCHING 80V 200MA 2NS DO-35	03334	BAV10 SELECTED
CR9	1901-0050	3	1	DIODE-SWITCHING 80V 200MA 2NS DO-35	03334	BAV10 SELECTED
CR10	1901-1070	9	1	DIODE-PIN 110V	02062	
CR11	1901-0535	9	1	DIODE-SCHOTTKY SM SIG	02062	
CR12	1901-1070	9	1	DIODE-PIN 110V	02062	
CR13	1901-0535	9	1	DIODE-SCHOTTKY SM SIG	02062	
CR14	1901-0050	3	1	DIODE-SWITCHING 80V 200MA 2NS DO-35	03334	BAV10 SELECTED
L1	9100-3562	8	1	INDUCTOR RF-CH-MLD 4.7UH +-5% .166D-INX.	03273	15M471J
L2	9100-1624	9	1	INDUCTOR RF-CH-MLD 30UH +-5% .166D-INX.3	03273	15M302J
L3	9100-0539	3	1	INDUCTOR RF-CH-MLD 10UH +-5% .166D-INX.3	03273	15M102J
L4	9140-0266	7	1	INDUCTOR RF-CH-MLD 1.8UH +-5% .166D-INX.	03273	15M181J

HP Part Number 08590-60158
BW Filter

Reference Designation	HP Part Number	C D	Qty	Description	Mfr Code	Mfr Part Number
L5	9100-1624	9	1	INDUCTOR RF-CH-MLD 30UH +-5% .166D-INX.3	03273	15M302J
L6	9100-0539	3	1	INDUCTOR RF-CH-MLD 10UH +-5% .166D-INX.3	03273	15M102J
L7	08590-80120	8	1		28480	08590-80120
L8	9100-0539	3	1	INDUCTOR RF-CH-MLD 10UH +-5% .166D-INX.3	03273	15M102J
L9	9140-0453	4	1	INDUCTOR RF-CH-MLD 6.8UH +-5% .166D-INX.	03273	15M-681J
L10	9140-0142	8	1	INDUCTOR RF-CH-MLD 2.2UH +-10% .105D-INX	03273	10M221K
L11	9100-0539	3	1	INDUCTOR RF-CH-MLD 10UH +-5% .166D-INX.3	03273	15M102J
L12	9140-0266	7	1	INDUCTOR RF-CH-MLD 1.8UH +-5% .166D-INX.	03273	15M181J
L13	9100-1624	9	1	INDUCTOR RF-CH-MLD 30UH +-5% .166D-INX.3	03273	15M302J
L14	9100-0539	3	1	INDUCTOR RF-CH-MLD 10UH +-5% .166D-INX.3	03273	15M102J
L15	08590-80120	8	1		28480	08590-80120
L16	9100-0539	3	1	INDUCTOR RF-CH-MLD 10UH +-5% .166D-INX.3	03273	15M102J
L17	9140-0453	4	1	INDUCTOR RF-CH-MLD 6.8UH +-5% .166D-INX.	03273	15M-681J
L18	9100-1633	0	1	INDUCTOR RF-CH-MLD 68UH +-5% .166D-INX.3	03273	15M682J
L19	9140-0144	0	1	INDUCTOR RF-CH-MLD 4.7UH +-10% .105D-INX	03273	10M471K
Q1	1854-0345	8	1	TRANSISTOR NPN 2N5179 SI TO-72 PD=200MW	02037	2N5179
Q2	1854-0477	7	1	TRANSISTOR NPN 2N2222A SI TO-18 PD=500MW	02037	2N2222A
Q3	1853-0007	7	1	TRANSISTOR PNP 2N3251 SI TO-18 PD=360MW	02037	2N3251
Q4	1853-0007	7	1	TRANSISTOR PNP 2N3251 SI TO-18 PD=360MW	02037	2N3251
Q5	1853-0007	7	1	TRANSISTOR PNP 2N3251 SI TO-18 PD=360MW	02037	2N3251
Q6	1855-0267	5	1	TRANSISTOR J-FET N-CHAN D-MODE TO-92 SI	02037	
Q7	1854-0477	7	1	TRANSISTOR NPN 2N2222A SI TO-18 PD=500MW	02037	2N2222A
Q8	1853-0007	7	1	TRANSISTOR PNP 2N3251 SI TO-18 PD=360MW	02037	2N3251
Q9	1853-0007	7	1	TRANSISTOR PNP 2N3251 SI TO-18 PD=360MW	02037	2N3251
Q10	1853-0007	7	1	TRANSISTOR PNP 2N3251 SI TO-18 PD=360MW	02037	2N3251
Q11	1855-0267	5	1	TRANSISTOR J-FET N-CHAN D-MODE TO-92 SI	02037	
Q12	1853-0007	7	1	TRANSISTOR PNP 2N3251 SI TO-18 PD=360MW	02037	2N3251
R1	0757-0444	1	1	RESISTOR 12.1K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R2	0698-3156	2	1	RESISTOR 14.7K 1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R3	0698-7205	0	1	RESISTOR 51.1 +-1% .05W TF TC=0+-100	00746	CRB20
R4	0757-0439	4	1	RESISTOR 6.81K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R5	0698-7205	0	1	RESISTOR 51.1 +-1% .05W TF TC=0+-100	00746	CRB20
R6	0757-1094	9	1	RESISTOR 1.47K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R7	0757-0401	0	1	RESISTOR 100 +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R8	8159-0005	0	1	RESISTOR 0 CWM	01339	L-2007-1
R9	0698-3431	6	1	RESISTOR 23.7 1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R10	0757-0405	4	1	RESISTOR 162 +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R11	0757-0401	0	1	RESISTOR 100 +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R12	0698-0082	7	1	RESISTOR 464 1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R13	0757-0447	4	1	RESISTOR 16.2K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R14	0757-0180	2	1	RESISTOR 31.6 +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R15	0757-0440	7	1	RESISTOR 7.5K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R16	0698-7205	0	1	RESISTOR 51.1 +-1% .05W TF TC=0+-100	00746	CRB20
R17	0757-0419	0	1	RESISTOR 681 +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R18	0698-7216	3	1	RESISTOR 147 +-1% .05W TF TC=0+-100	00746	CRB20
R19	0698-3442	9	1	RESISTOR 237 1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R20	0698-3440	7	1	RESISTOR 196 1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R21	0698-3152	8	1	RESISTOR 3.48K 1% .125W TF TC=0+-100	00746	CRB14 OR CRB25

**Indicates factory-selected value*

HP Part Number 08590-60158

BW Filter

Reference Designation	HP Part Number	C D	Qty	Description	Mfr Code	Mfr Part Number
R22	0698-3154	0	1	RESISTOR 4.22K 1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R23	0757-0442	9	1	RESISTOR 10K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R24	0698-3136	8	1	RESISTOR 17.8K 1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R25	0757-0458	7	1	RESISTOR 51.1K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R26	2100-3056	8	1	RESISTOR-TRMR 5K 10% TKF SIDE-ADJ 17-TRN	03744	3006P-DM3-502
R27	0757-0442	9	1	RESISTOR 10K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R28	0698-3154	0	1	RESISTOR 4.22K 1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R29	0757-0442	9	1	RESISTOR 10K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R30	0757-0444	1	1	RESISTOR 12.1K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R31	2100-3052	4	1	RESISTOR-TRMR 50 10% TKF SIDE-ADJ 17-TRN	03744	3006P-DM3-500
R32	0757-0443	0	1	RESISTOR 11K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R33	0757-0428	1	1	RESISTOR 1.62K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R34	0698-7212	9	1	RESISTOR 100 +-1% .05W TF TC=0+-100	00746	CRB20
R35	0698-7205	0	1	RESISTOR 51.1 +-1% .05W TF TC=0+-100	00746	CRB20
R36	0698-7205	0	1	RESISTOR 51.1 +-1% .05W TF TC=0+-100	00746	CRB20
R37	0757-0288	1	1	RESISTOR 9.09K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R38	0698-0083	8	1	RESISTOR 1.96K 1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R39	0757-0401	0	1	RESISTOR 100 +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R40	0698-0082	7	1	RESISTOR 464 1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R41	0757-0447	4	1	RESISTOR 16.2K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R42	0757-0180	2	1	RESISTOR 31.6 +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R43	0757-0440	7	1	RESISTOR 7.5K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R44	0698-7205	0	1	RESISTOR 51.1 +-1% .05W TF TC=0+-100	00746	CRB20
R45	0757-0419	0	1	RESISTOR 681 +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R46	0698-7216	3	1	RESISTOR 147 +-1% .05W TF TC=0+-100	00746	CRB20
R47	0698-3442	9	1	RESISTOR 237 1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R48	0698-3441	8	1	RESISTOR 215 1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R49	0698-3152	8	1	RESISTOR 3.48K 1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R50	0698-3154	0	1	RESISTOR 4.22K 1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R51	0757-0442	9	1	RESISTOR 10K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R52	0698-3136	8	1	RESISTOR 17.8K 1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R53	0757-0458	7	1	RESISTOR 51.1K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R54	0757-0442	9	1	RESISTOR 10K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R55	0698-3154	0	1	RESISTOR 4.22K 1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R56	0757-0442	9	1	RESISTOR 10K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R57	0757-0444	1	1	RESISTOR 12.1K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R58	0757-0443	0	1	RESISTOR 11K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R59	0698-3154	0	1	RESISTOR 4.22K 1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R60	0757-0346	2	1	RESISTOR 10 +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R61	0698-3441	8	1	RESISTOR 215 1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R62	0698-7205	0	1	RESISTOR 51.1 +-1% .05W TF TC=0+-100	00746	CRB20
R63	0698-7212	9	1	RESISTOR 100 +-1% .05W TF TC=0+-100	00746	CRB20
R64	0698-3444	1	1	RESISTOR 316 1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R65	0757-0346	2	1	RESISTOR 10 +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R66	0757-0401	0	1	RESISTOR 100 +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R67	0757-0401	0	1	RESISTOR 100 +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R68	0757-0442	9	1	RESISTOR 10K +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R69	0698-3152	8	1	RESISTOR 3.48K 1% .125W TF TC=0+-100	00746	CRB14 OR CRB25

HP Part Number 08590-60158

BW Filter

Reference Designation	HP Part Number	C D	Qty	Description	Mfr Code	Mfr Part Number
R70	0698-3156	2	1	RESISTOR 14.7K 1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R71	0698-0083	8	1	RESISTOR 1.96K 1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R72	0757-0346	2	1	RESISTOR 10 +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R73	0757-0346	2	1	RESISTOR 10 +-1% .125W TF TC=0+-100	00746	CRB14 OR CRB25
R74	0698-7264	1	1	RESISTOR 14.7K +-1% .05W TF TC=0+-100	00746	CRB20
TP1	1252-3104	7	1	CONN-POST TYPE .100-PIN-SPCG 2-CONT	02946	68016-102
TP2	1252-3104	7	1	CONN-POST TYPE .100-PIN-SPCG 2-CONT	02946	68016-102
TP3	0360-2050	8	1	CONNECTOR-SGL CONT	04055	
TP4	1252-3104	7	1	CONN-POST TYPE .100-PIN-SPCG 2-CONT	02946	68016-102
TP5	1252-3104	7	1	CONN-POST TYPE .100-PIN-SPCG 2-CONT	02946	68016-102
TP6	0360-2050	8	1	CONNECTOR-SGL CONT	04055	
TP7	0360-2050	8	1	CONNECTOR-SGL CONT	04055	
TP8	0360-2050	8	1	CONNECTOR-SGL CONT	04055	
TP9	0360-2050	8	1	CONNECTOR-SGL CONT	04055	
U1	1826-0915	9	1	IC OP AMP LOW-BIAS-H-IMPD 8-DIP-C PKG	01698	TL071ACJG (PER HP DWG)
VR1	1902-0954	8	1	DIODE-ZNR 6.8V 5% DO-35 PD=.4W TC=+.057%	02037	
Y1	0410-2118	6	1	CRYSTAL-QUARTZ 21.4MHz SET OF 4	03747	
Y2	0410-2118	6	1	CRYSTAL-QUARTZ 21.4MHz SET OF 4	03747	

**Indicates factory-selected value*